

eGauge XML API

(v1.2)

eGauge Systems LLC

March 31, 2012

1 Overview

This document describes how to read raw XML data from an eGauge device using CGI queries. This document applies to firmware versions v1.00 or newer. There are two types of queries: instantaneous and stored data queries. The former reads the most recent values of all measured data, whereas the latter reads (portions of) the historical data stored in a database built into the eGauge device.

Numeric data is returned either as integer strings or floating-point strings. The underlying format for integer strings is either unsigned 32-bit integers (U32) or signed 64-bit integers (S64). The range of U32 extends from 0 to 4,294,967,295. The range of S64 extends from -9,223,372,036,854,775,808 to 9,223,372,036,854,775,807. The underlying format for floating-point strings is the IEEE-754 64-bit floating point format.

S64 values are circular: after reaching the maximum positive value, they wrap around to the smallest negative value (and vice versa). Also note that JavaScript cannot natively handle 64-bit values and care must be taken to avoid overflows.

2 Instantaneous Data

Instantaneous data is updated once a second. It is fetched via the URI reference:

```
/cgi-bin/egauge?params
```

The possible values for *params* are described in the next section. Multiply query-parameters can be specified by separating them with an ampersand (e.g., **v1&tot** to specify both **v1** and **tot**).

2.1 Query Parameters

Parameter:	Type:	Description:
tot	n/a	Requests that the totals and virtual registers calculated from the physical registers be included in the output.
noteam	n/a	Requests that only locally measured values be reported. The values of any registers acquired from remote devices are omitted.

teamstat	n/a	Requests that the teaming status be reported.
v1	n/a	Requests that the output be in v1.00 format as opposed to the legacy v0.01 format. If a device is configured to read out any remote devices, then v1.00-output is the default.
inst	n/a	Requests that, along with the normal register values, the instantaneous rate-of-change of each register also be reported.

2.2 Instantaneous Data (v1.00 format)

A sample output for the v1.00 format is shown in Figure 1.

```
<?xml version="1.0" encoding="UTF-8" ?>
<data serial="0x78666e4d">
  <ts>1284607004</ts>
  <r t="P" n="Grid"><v>5196771697</v></r>
  <r t="P" n="Solar"><v>21308130148</v></r>
  <r t="P" n="Grg&Bth (PHEV)"><v>17601054087</v></r>
</data>
```

Figure 1: Example of instantaneous data with **v1** query parameter.

The instantaneous data query returns a single element enclosed by **data** start and end tags. The **data** element may have a **serial** attribute which specifies the configuration serial number as a hexa-decimal string. This serial number is guaranteed to change whenever a change is made to the device configuration. Thus, the serial-number can be used to detect configuration-changes.

Within the **data** element, the following elements may appear:

Element Name:	Type:	Description:
ts	Integer (U32)	The device-local time at which the reported measurements were obtained. This is a UNIX timestamp (seconds since start of January 1st, 1970 UTC).
r	Struct	There is one r element per register configured in the device. Attribute t specifies the code identifying the register's type (see Section 2.2.1). Attribute n specifies the register name, which may contain HTML entities to encode special characters. Attribute rt may be set to the string total to indicate that the register is a total or virtual register whose value has been calculated from the physical registers. Two sub-elements may appear for each r element: v and i .
v	Integer (S64)	A cumulative register value expressed in a type-specific unit. Subtracting two consecutive readings and dividing by the number of seconds elapsed between the samples gives the average rate of change for the register.
i	Float	The average rate of change of the register value as measured for the most recent one-second interval.

2.2.1 Register Types

The table below specifies the code used to identify the register type, the physical quantity represented by the code, and the unit of measurement for the rate of change of the register values.

Code:	Physical Quantity:	Unit for rate of change:
P	Power	W (Watt)
S	Apparent Power	VA (Volt-Ampère)
V	Voltage	mV (milli-Volt)
I	Current	mA (milli-Ampère)
F	Frequency	mHz (milli-Hertz)
T	Temperature	mC (milli-Centigrade Celsius)
Q	Mass-flow	g/s (gram per second)
v	Speed	m/s (meter per second)
R	Resistance	Ω (Ohm)
Ee	Irradiance	W/m^2 (Watts per square meter)
#	Numeric	(unit-less)

New register-type codes may be added over time. Software processing the eGauge XML data should be written such that it degrades gracefully when encountering an unknown register-type code.

Note that the above units apply to the rate-of-change of a register. The *value* of a register is the time-integral over the rate-of-change, so the register's unit is the above unit multiplied by time in seconds. For example, for power, the rate-of-change unit is Watts, and therefore the register value is Watt-seconds (which is equivalent to Joules). Watt-seconds can be converted to kilo-Watt-hours (kWh) by dividing by 3,600,000.

2.3 Instantaneous Data (legacy v0.01 format)

A sample output in the legacy format (v0.01) is shown in Figure 2. Compared to the v1.00-format, this format is more verbose and is limited to reporting registers of type **P** (power). Registers with other types are *omitted* in this format to maintain backwards-compatibility.

The instantaneous data query returns a single element enclosed by **measurements** start and end tags. Like the **data** element, **measurements** may have a **serial** attribute indicating the configuration serial number.

Within the **measurements** element, the following elements may appear:

Element Name:	Type:	Description:
timestamp	Integer (U32)	The device-local time at which the reported measurements were obtained. This is a UNIX timestamp.
meter	Struct	There is one meter element per register configured in the device. Attribute title gives the register-name. Attribute type may be set to the string total to indicate that the meter is a calculated total. Three sub-elements may appear for each meter element: energy , energyWs , and power .
energy	Float	A cumulative energy meter value expressed in units of kilo-Watt-hours (kWh). Subtracting two consecutive readings and dividing by the amount of time elapsed between the samples (expressed in hours) gives average power in kilo-Watts (kW).

energyWs	Integer (S64)	Same as energy , but expressed in units of Watt-seconds (Ws).
power	Float	The average power measured for the most recent one-second interval. Note that this may be positive or negative, depending on the direction of the power-flow.
frequency	Float	Frequency in Hertz as measured on one of the configured voltage taps (L1, L2, or L3). It is presently unspecified which of the configured voltage taps is used to measure frequency.
voltage	Float	RMS voltage in Volts. These elements appear in lowest to highest voltage-channel order.
current	Float	RMS current in Amperes. These elements appear in lowest to highest current-channel order.
cpower	Float	The current value of a power component. Each voltage/current product configured for the device gives rise to one component power. Attribute src identifies which register the component contributes to. Attributes i and u identify the voltage and current channels used to calculate this power. The channel-assignment is device-specific and left unspecified by this document.

2.4 Team Status

An eGauge device configured to read out remote devices is part of a team whose members include the device itself and all remote devices.

The status of such a team can be obtained by passing the **teamstat** query parameter. The returned status indicates the availability and status of the configured registers, some of which may be acquired from one or more remote devices. A sample output of the team status format is shown in Figure 3.

The team status is returned in a single element enclosed by **status** start and end tags. Within the **status** element, the following elements may appear:

Element Name:	Type:	Description:
lag	Integer (U32)	The amount of time by which the reported instantaneous data is behind real time. This lag is normally reported in in units of milli-seconds, as indicated by a value of ms for the attribute unit . Ideally, this lag should be close to zero, but may be larger when fetching data from remote devices that are slow to reach or that are temporarily unavailable.
reg	Struct	There is one such element for each register defined for the device. These elements appear in the same order as the register (r) tags in the v1.00 instantaneous data format. The sub-elements name , available , last_update , excess , and last_val may appear inside this element.
available	Boolean	Indicates whether the (remote-)device supplying the data for this register is currently reachable. A value of 1 indicates the device is reachable, a value of 0 indicates that the device is unreachable.
last_update	Integer (U32)	UNIX timestamp of when the value for this register was updated last.
max_rate	Float	Maximum rate of change observed for this register.
leak_rate	Float	Rate at which the register catches up to the true value when there is an excess (see next element).
excess	Integer (S64)	A non-zero value for this element indicates that the device supplying the data for this register was unreachable some time ago and the amount by which the current register-value is off from the true value.
last_val	Integer (S64)	The last value recorded for this register.

```
<?xml version="1.0" encoding="UTF-8" ?>
<measurements serial="0x7866e4d">
  <timestamp>1284607004</timestamp>
  <cpower src="Grg&Bth (PHEV)" i="11" u="1">-988.9</cpower>
  <cpower src="Solar" i="5" u="8">-1.9</cpower>
  <cpower src="Grid" i="1" u="0">604.70</cpower>
  <cpower src="Grid" i="3" u="1">1621.5</cpower>
  <meter title="Grid">
    <energy>1443.5</energy>
    <energyWs>5196771697</energyWs>
    <power>2226.2</power>
  </meter>
  <meter title="Solar">
    <energy>5918.9</energy>
    <energyWs>21308130148</energyWs>
    <power>-1.9</power>
  </meter>
  <meter title="Grg&Bth (PHEV)">
    <energy>4889.2</energy>
    <energyWs>17601054087</energyWs>
    <power>-988.9</power>
  </meter>
  <frequency>59.98</frequency>
  <voltage>119.0</voltage>
  <voltage>118.3</voltage>
  <current>5.495</current>
  <current>14.152</current>
  <current>0.223</current>
  <current>0.136</current>
</measurements>
```

Figure 2: Example of instantaneous data (legacy v0.01 format).

```

<?xml version="1.0" encoding="UTF-8" ?>
<status>
  <lag unit="ms">227</lag>
  <reg>
    <name>Grid</name>
    <available>1</available>
    <last_update>1312472842</last_update>
    <excess>0</excess>
    <last_val>0</last_val>
  </reg>
  :
  <reg>
    <name>Solar</name>
    <available>0</available>
    <last_update>1312472842</last_update>
    <excess>0</excess>
    <last_val>0</last_val>
  </reg>
</status>

```

Figure 3: Example of team status data (**teamstat** query parameter).

3 Stored Data

Stored data is updated once a minute. It is fetched via the URI reference:

```
/cgi-bin/egauge-show?params
```

This query returns energy data as rows of columns. Each row reports data for a specific point in time. The row consists of a fixed number of columns, with one column per configured register. Various query parameters *params* can be specified to select which data to retrieve and what format to return it in.

3.1 Query Parameters

Parameter:	Type:	Description:
a	n/a	Requests that the totals and virtual registers calculated from the physical register values be included as the first columns in each row. These values are calculated according to the Totaling and Virtual Register rules configured for the device.
b	n/a	Requests the output be returned in the data backup format.
c	n/a	Requests the output be returned in CSV (comma-separated value) format.
m	n/a	Specifies that n and s parameters are specified in units of minutes.
h	n/a	Specifies that n and s parameters are specified in units of hours.

d	n/a	Specifies that n and s parameters are specified in units of days.
C	n/a	Specifies that the returned data be delta-compressed. That is, after the first row of data, each subsequent row's columns are expressed as a difference relative to the previous row's column-values.
n	Integer (U32)	Specifies the maximum number of rows to be returned.
s	Integer (U32)	Specifies the number of rows to skip after outputting a row. For example, <code>h&s=23</code> would skip 23 hours worth of data after a row is output, and would be equivalent to <code>d</code> .
f	Integer (U32)	Specifies the timestamp of the first row to be returned.
t	Integer (U32)	Specifies the timestamp of the last row to be returned.
w	Integer (U32)	Specifies the timestamp of the first row to be returned. If the timestamp lies in the future, the query will complete immediately returning an empty data element whose wait.time attribute indicates how many seconds have to elapse before the desired row is available.
T	Integer-list (U32)	Specifies a list of timestamps, ordered by decreasing value (younger to older) for which to return data rows.
Z	string	Specifies the time-zone to use when exporting CSV data. The format of this string is described at http://www.opengroup.org/onlinepubs/009695399/basedefs/xbd_chap08.html under environment variable TZ . As of firmware v1.12, it is possible to omit the value for this parameter. In this case, the device converts time-stamps using the device-local time-zone (specified through setting "Time Zone" in the "Date & Time" dialog).

3.2 Returned XML Data

A sample output for this query using parameters `m&n=3` is shown in Figure 4.

```
<?xml version="1.0" encoding="UTF-8" ?>
<group serial="0x37cdd096">
<data columns="3" time_stamp="0x4c9197e4" time_delta="60" epoch="0x47395980">
  <cname t="P">Grid</cname>
  <cname t="P">Solar</cname>
  <cname t="P">Grg&Bth (PHEV)</cname>
  <r><c>5203642184</c><c>21308125431</c><c>17598056700</c></r>
  <r><c>5203503484</c><c>21308125526</c><c>17598116405</c></r>
  <r><c>5203368999</c><c>21308125626</c><c>17598176060</c></r>
</data>
</group>
```

Figure 4: Example of stored data.

The stored data query returns a single element enclosed by **group** start and end tags. Just like the **data** element of the instantaneous response, the **group** element may have a **serial** attribute indicating the configuration serial number.

Within the **group** element, the following elements may appear:

Element Name:	Type:	Description:
data	Struct	One such element appears for each consecutive sequence of data rows. Attribute columns specifies the number of columns in each row. Attribute time_stamp specifies the UNIX timestamp (in hex) for the first row. Attribute time_delta specifies the number of seconds to be subtracted to get the next row's timestamp. Attribute epoch specifies the UNIX timestamp (in hex) of the time at which recording started. Attribute delta is equal to true if the data rows are delta-encoded (see below). Attribute wait_time specifies how many seconds have to elapse before the timestamp specified by the w parameter is available for reading.
cname	String	Specifies the register-name of a column in order of increasing column. This element may only appear in the first data element. In subsequent data elements, the register names must remain the same as for the first one. This element may have a t attribute which identifies the type of the register (see 2.2.1). If the t attribute is not present, a type-code of P (power) should be assumed.
r	Struct	Contains one row of data.
c	Integer (S64)	An individual cumulative register value. This value must be interpreted according to the register-type specified (or implied) by the corresponding cname declaration.